

Features

- Carbon Monoxide detection device compliant with UL 2075
- 8 year lifespan with built in end of life indication
- Low profile
- Walk Test mode allows for fast easy validation of sensor operation
- Reliable detection technology
- LED Alarm Indicator
- Product includes a 5 year warranty



Description

The PAD100-CD is an Analog Addressable carbon monoxide (CO) sensor compatible with any fire alarm control panel that has the Potter Addressable Device (PAD) protocol. The CO sensing portion utilizes a proven electrochemical sensor for accurate detection of CO gas for life safety applications. The sensor and base (not included) are made of a durable plastic in an off white to blend in with the ceiling.

The PAD100-CD is listed to comply with the requirements of UL 2075. The sensor and the control panel communicate over a proven and robust digital communication path and the system analyzes the information at the particular device. The total polling speed is less than five (5) seconds, well under the UL requirements.

The sensor is compatible with any of the PAD series sensor bases and simply twists on. The PAD100-CD is addressed using DIP switches in the rear of the sensor and can be easily programmed in the field without special tools.

Setting the Address

Each addressable device on the SLC loop must have a unique address from 1 to 127 to function properly. The address is set using DIP switches.

Before connecting a device to the SLC loop, take the following precautions to prevent potential damage to SLC or device. Verify the following:

1. Power to the device is removed
2. Field wiring is correctly installed.
3. Field wiring has no open or short circuits.

Technical Specifications

Operating Voltage	24 VDC
Alarm indicator	1 LED
Alarm set-point range	70 ppm, 150 ppm, 400 ppm
Installation temperature range	32 to 120 °F / 0 to 49 °C
Operating relative humidity range	0% to 93% (Non-condensing)
Start-up time	Max. 1 sec.
Maximum number of addresses per loop	127
Maximum number of lighted indicators in alarm per loop	30
Color	Eggshell White
Weight (without base)	92g (3.25oz)
Dimensions (without base)	Height: 1.43 in (36mm) Diameter: 3.93 inches (100mm)

Operation

The PAD100-CD is an analog addressable sensor that uses one address on the Signaling Line Circuit (SLC) of a compatible fire alarm control panel. The unit communicates with the control panel as it is polled. The LED flashes every time the unit is polled and they will latch steady if the unit is in an active status. The polling LED can be turned off if desired for less conspicuous operation.

The PAD100-CD with the PAD100-4DB or PAD100-6DB has a low profile of less than two (2) inches to blend into the surrounding environment.

Detection Levels

The PAD100-CD will provide alarm reports at these required levels:

Alarm set-point

70 ppm for 2 hours

150 ppm for 30 min

400 ppm for 10 minutes

Compatible Bases

All bases will mount on a single gang, double gang, octagon, 4" square or mud ring electrical box.

Device	Description	Stock No.
PAD100-4DB	4" Standard Base	3992731
PAD100-6DB	6" Standard Base	3992732
PAD100-IB	6" base with an isolator module included.	3992730
PAD100-RB	6" base with one Form-C relay contact. 2A @ 30VDC, 0.5A @ 125VAC	3992728
PAD100-SB	6" base with sounder module included. Sound pattern is provided from external source.	3992729

Ordering Information

Model	Description	Stock No.
PAD100-CD	Carbon Monoxide Detector	3992736